

OPTIONS EVALUATION REPORT (OER)



Line 8C-8J - Refurb

OER- N2496 revision 1.0

Ellipse project no(s):

TRIM file: [TRIM No]

Project reason: Reliability - To meet overall network reliability requirements

Project category: Prescribed - Replacement

Approvals

Author	Lakshman Ganesharajah	Transmission Line and Cables Analyst
Endorsed	Charles Kurniawan	Transmission Lines and Cables Asset Manager
	Debashis Dutta	Asset Analytics and Insights Manager
Approved	Lance Wee	Head of Asset Management
Date submitted for approval	13 October 2021	

Change history

Revision	Date	Amendment
0	13/10/2021	Initial Issue
1	12/11/2021	Minor Update

Warning: A printed copy of this document may not be the current version. Please refer to the Wire to verify the current version.

Executive summary

Line 8C/8J is a double circuit, steel tower 330kV transmission line with a route length of 58.9km, and connects Dumaresq and Sapphire Substations. The transmission line is a key link in the east coast network and is on the QNI transmission path which links the NSW and QLD regions of the National Electricity Market.

The line was constructed in 2000 to as part of the interconnector between New South Wales and Queensland transmission networks, and consists of 143 structures. It mainly traverses rural agricultural land, bushland areas, and crosses the some minor roads and waterways along the route.

The line was amongst the first constructed utilising Non-Ceramic Insulators (NCI) within the TransGrid network and these are now approaching the end of their service life. The sample test results have shown a large reduction in hydrophobicity (i.e. ability of the insulator to resist the ingress of moisture), reduction in rod to housing adhesion and corona activity at the end fitting to housing interface, due to degradation and older design of this interface, after 21 years in service.

Majority of the line has Non Ceramic Insulators (NCIs) installed, and a health assessment indicates that these insulators will reach end of life at around 2025. This is consistent with the current industry practice to restrict service life of NCIs at Extra High Voltage to 25 years due to corona ageing effects on the silicone housing.

Recent inspection data and detailed asset condition analysis have identified that 140 of the 143 structures on Line 8C/8J have condition issues which require refurbishment to address its health and maintain appropriate risk levels across the network.

The assessment of the options considered to address the need/opportunity appears in Table 1.

There is a need to remediate these issues to:

- > Manage network safety risk levels “As-Low-As Reasonably-Practicable” in accordance with the regulation obligations and TransGrid’s business risk appetite. Under the Electricity Supply (Safety and Network Management) Regulation 2014 Section 5 ‘A network operator must take all reasonable steps to ensure that the design, construction, commissioning, operation and decommissioning of its network (or any part of its network) is safe’; and
- > Provide economic benefit to consumers through reduction in safety and bushfire risks.

Table 1 - Evaluated options

Option	Description	Direct capital cost (\$m)	Network and corporate overheads (\$m)	Total capital cost ¹ (\$m)	Weighted NPV (PV, \$m)	Rank
Option A	Refurbish components that meet primary condition criteria only	7.61	0.67	8.28	27.50	1

The preferred option is Option A as it has positive weighted NPV result of the technically and commercially feasible option. Options considered and not progressed are stated in section 3.3.

It is therefore recommended that Option A be scoped in detail and progressed from DG1 to DG2.² In consideration of the delivery requirements and the economic benefit NPV analysis for the need, its optimal timing is 2025/2026.

¹ Total capital cost is the sum of the direct capital cost and network and corporate overheads. Total capital cost is used in this OER for all analysis.

1. Need/opportunity

Line 8C/8J is a double circuit, steel tower 330kV transmission line with a route length of 58.9km, and connects Dumaresq and Sapphire Substations. The transmission line is a key link in the east coast network and is on the QNI transmission path which links the NSW and QLD regions of the National Electricity Market.

The line was amongst the first constructed utilising Non-Ceramic Insulators (NCI) within the TransGrid network and these are now approaching the end of their service life. The sample test results have shown a large reduction in hydrophobicity (ie ability of the insulator to resist the ingress of moisture), reduction in rod to housing adhesion and corona activity at the end fitting to housing interface, due to degradation and older design of this interface, after 21 years in service.

Majority of the line has Non Ceramic Insulators (NCIs) installed, and a health assessment predicts that these will reach end of life at around 2025. This is consistent with current industry practise to restrict service life of NCIs at Extra High Voltage to 25 years due to corona ageing effects on the silicone housing.

Recent inspection data and detailed asset condition analysis have identified that 140 of the 143 structures on Line 8C/8J have condition issues which require refurbishment to address its health and maintain appropriate risk levels across the network.

Other issues on the line include:

- > Deterioration of public safety – Danger signs, which could lead to unauthorised access to the structures.
- > Deterioration on tower components relating to public safety such as marker balls, climbing deterrents and signage.
- > Broken strands on earthwire bonding – failure of bond can result in uncontrolled discharge or contact with electricity.

There is a need to remediate these issues to:

- > Manage network safety risk levels “As-Low-As Reasonably-Practicable” in accordance with the regulation obligations and TransGrid’s business risk appetite. Under the Electricity Supply (Safety and Network Management) Regulation 2014 Section 5 ‘A network operator must take all reasonable steps to ensure that the design, construction, commissioning, operation and decommissioning of its network (or any part of its network) is safe’; and
- > Provide economic benefit to consumers through reduction in safety and bushfire risks.

Appendix B provides a summary of the number of structures with condition issues within each asset component category. The figures are based on the Transmission Line Refurbishment Criteria document.

2. Related needs/opportunities

- > Need N2497: Line 8C/8E Refurbishment
- > Need N2498: Line 8L/8M Refurbishment

² DG stands for ‘decision gate’ that forms a part of TransGrids investment decision process.

3. Options

The base case for this assessment is a ‘do nothing’ scenario, where the assets are left in service until they fail and require replacement. In addition to the base case, one refurbishment option has been considered.

3.1 Base case

It is noted that a ‘run to fail’ scenario, where the issues are addressed through increased asset monitoring and preventative maintenance tasks, is not a valid base case for this Need. The condition issues on the asset have already been identified through maintenance inspections, and increasing the frequency of inspections to monitor the condition issues will not necessarily address them.

The base case will instead be defined as a ‘do nothing’ scenario, where the assets are left in service until they fail and require replacement. The replacement cost has been captured in the NPV assessment under financial risk cost.

3.2 Options evaluated

Option A — Refurbish components that meet primary condition criteria only. [\[NOSA-N2496, OFS-N2496A\]](#)

It is estimated that this option would cost \$8.28 million ± 25% in \$2020-21.

This project is expected to be completed within the 2024 – 2028 regulatory period and completed within 30 months following DG1.

3.3 Options considered and not progressed

The following options were considered but not progressed:

Table 2 Options considered but not progressed

Option	Reason for not progressing
Increased inspections	The condition issues have already been identified and cannot be rectified through increased inspections, and therefore is not technically feasible.
Elimination of all associated risk	This can only be achieved through retirement and decommissioning of the associated assets which may lead to reliability issue. Therefore, it is considered not technically feasible.
New transmission line	Due to significant costs of this option, a new double circuit 330 kV transmission line is not considered commercially feasible.
Non-network solutions	TransGrid does not consider non-network options to be commercially and technically feasible to assist with meeting the identified need, as non-network options will not mitigate the environment (bushfire) and safety posed as a result of corrosion-related asset deterioration.

4. Evaluation

4.1 Commercial evaluation methodology

The economic assessment undertaken for this project includes three scenarios that reflect a central set assumptions based on current information that is most likely to eventuate (central scenario), a set of assumptions that give rise to a lower bound for net benefits (lower bound scenario), and a set of assumptions that give rise to an upper bound on benefits (higher bound scenario).

Warning: A printed copy of this document may not be the current version. Please refer to the Wire to verify the current version.

Assumptions for each scenario are set out in the table below.

Table 3 Scenarios

Parameter	Central scenario	Lower bound scenario	Higher bound scenario
Discount rate	4.8%	7.37%	2.23%
Capital cost	100%	125%	75%
Risk costs benefit	100%	75%	125%
Scenario weighting	50%	25%	25%

Parameters used in this commercial evaluation are set out in the table below

Table 4 Parameters used in the NPV evaluation

Parameter	Parameter Description	Value used for this evaluation
Discount year	Year that dollar values are discounted to	2020/2021
Base year	The year that dollar value outputs are expressed in real terms	2020/2021 dollars
Period of analysis	Number of years included in economic analysis with remaining capital value included as terminal value at the end of the analysis period.	25 years
Expected asset life	Period of depreciation of the asset	35 years
ALARP disproportionality	Multiplier of the environmental and safety related risk cost included in NPV analysis to demonstrate implementation of obligation to reduce to ALARP.	Refer to section 4.3 for details.

The capex figures in this OER do not include any real cost escalation.

4.2 Commercial evaluation results

The commercial evaluation of the technically feasible options is set out in Table 5. Details appear in Appendix A.

Table 5 - Commercial evaluation (PV, \$ million)

Option	Capital Cost PV	Central scenario NPV	Lower bound scenario NPV	Higher bound scenario NPV	Weighted NPV	Ranking
Option A	6.57	23.87	7.77	54.49	27.50	1

4.3 ALARP evaluation

TransGrid manages and mitigates bushfire and safety risk to ensure they are below risk tolerance levels or 'As Low As Reasonably Practicable' ('ALARP'), in accordance with the regulation obligations and TransGrid's business risk

Warning: A printed copy of this document may not be the current version. Please refer to the Wire to verify the current version.

appetite. Under the Electricity Supply (Safety and Network Management) Regulation 2014 Section 5 ‘A network operator must take all reasonable steps to ensure that the design, construction, commissioning, operation and decommissioning of its network (or any part of its network) is safe.’ TransGrid maintains an Electricity Network Safety Management System (ENSMS) to meet this obligation.³

In its Network Risk Assessment Methodology, under the ALARP test with the application of a gross disproportionate factor⁴, the weighted benefits are expected to exceed the cost. TransGrid’s analysis concludes that the costs are less than the weighted benefits from mitigating bushfire and safety risks. The proposed investment will enable TransGrid to continue to manage and operate this part of the network to a safety and risk mitigation level of ALARP.

Evaluation of the above options has been completed in accordance with As Low As Reasonably Practicable (ALARP) obligations. The Network Safety Risk Reduction is calculated as 6 x Bushfire Risk Reduction + 6 x Safety Risk Reduction + 0.1 x Reliability Risk Reduction.

Results of the ALARP evaluation are set out in Table 6.

Table 6 - Reasonably practicable test (\$ million)

Option	Network Safety Risk Reduction	Annualised Capex	Reasonably Practicable? ⁵
A	0.71	0.49	Y

The result of the ALARP evaluation is that Option A meets the ALARP threshold.

4.4 Preferred option

Option A is the preferred option for the remediation of Line 8C-8J as it has positive weighted NPV result. Option A also meets the ALARP threshold. The optimal delivery date for this option is 2025/2026 based on the optimal timing analysis (see Section 5).

Capital and Operating Expenditure

The required capex expenditure is \$8.28 million.

Regulatory Investment Test

A regulatory investment test for transmission (RIT-T) is required as the estimated capital cost for the preferred option is above the threshold of \$6 million.

5. Optimal Timing

In consideration of the delivery requirements and the economic benefit NPV analysis for the need, its optimal timing is 2025/2026.

The test for optimal timing of the preferred option has been undertaken. The approach taken is to identify the optimal commissioning year for the preferred option where net benefits (including avoided risk costs and safety disproportionality tests) of the preferred option exceeds the annualised costs of the option. The optimal timing assessment considers the delivery requirements of the project and the estimated delivery timeline of three years in the OFS.

³ TransGrid’s ENSMS follows the International Organization for Standardization’s ISO31000 risk management framework which requires following hierarchy of hazard mitigation approach

⁴ The values of the disproportionality factors were determined through a review of practises and legal interpretations across multiple industries, with particular reference to the works of the UK Health and Safety Executive. The methodology used to determine the disproportionality factors in this document is in line with the principles and examples presented in the AER Replacement Planning Guidelines and is consistent with TransGrid’s Revised Revenue Proposal 2023/24-2027/28.

⁵ Reasonably practicable is defined as whether the annualised CAPEX is less than the Network Safety Risk Reduction.

Warning: A printed copy of this document may not be the current version. Please refer to the Wire to verify the current version.

The commencement year is determined based on the required project disbursement to meet the commissioning year based on the OFS.

The results of optimal timing analysis is:

- > Optimal commissioning year: 2025/2026
- > Commissioning year annual benefit: \$1.4 million
- > Annualised cost: \$0.49 million

Based on the optimal timing, the project is expected to be completed in the 2024-2028 Regulatory Period.

6. Recommendation

The preferred option is Option A, as it has the positive weighted NPV result and meets the ALARP threshold.

It is therefore recommended that this option be scoped in detail, so that it can be progressed from DG1 to DG2. Total project cost is \$8.28 million including an amount of \$0.5 million to progress the project from DG1 to DG2.

Appendix A – Option Summaries⁶

Project Description		Line 8C/8J Refurbishment	
Option Description		Option A - Refurbish components that meet primary condition criteria only	
Project Summary			
Option Rank	1	Investment Assessment Period	25
Asset Life	35	NPV Year	2021
Economic Evaluation			
NPV @ Central Benefit Scenario (PV, \$m)	23.87	Annualised CAPEX @ Central Benefit Scenario (\$m)	Annualised Capex - Standard (Business Case) 0.49
NPV @ Lower Bound Scenario (PV, \$m)	7.77	Network Safety Risk Reduction (\$m)	Network Safety Risk Reduction 0.71
NPV @ Higher Bound Scenario (PV, \$m)	54.49	ALARP	ALARP Compliant? Yes
NPV Weighted (PV, \$m)	27.50	Optimal Timing	Optimal timing (Business Case) 2026
Cost (Central Scenario)			
Direct Capex (\$m)		Network and Corporate Overheads (\$m)	
Total Capex (\$m)	8.28	Cost Capex (PV,\$m)	6.57
Terminal Value (\$m)	2.13	Terminal Value (PV,\$m)	0.52
Risk (Central Scenario)	Pre	Post	Benefit
Reliability (PV,\$m)	Reliability Risk (Pre) 0.00	Reliability Risk (Post) 0.00	Pre – Post 0.00
Financial (PV,\$m)	Financial Risk (Pre) 18.54	Financial Risk (Post) 4.75	Pre – Post 13.79
Operational/Compliance (PV,\$m)	Operational Risk (Pre) 0.00	Operational Risk (Post) 0.00	Pre – Post 0.00
Safety (PV,\$m)	Safety Risk (Pre) 0.00	Safety Risk (Post) 0.00	Pre – Post 0.00
Environmental (PV,\$m)	Environmental Risk (Pre) 20.36	Environmental Risk (Post) 5.19	Pre – Post 15.17
Reputational (\$m)	Reputational Risk (Pre) 1.28	Reputational Risk (Post) 0.33	Pre – Post 0.95
Total Risk (PV,\$m)	Total Risk (Pre) 40.19	Total Risk (Post) 10.27	Pre – Post 29.92
OPEX Benefit (PV,\$m)			OPEX Benefit 0.00
Other benefit (PV,\$m)			Incremental Net Benefit 0.00
Total Benefit (PV,\$m)			Business Case Total Benefit 29.92

Commissioning year annual benefit (\$k):

1396.34

⁶ Figures may not add due to rounding

Warning: A printed copy of this document may not be the current version. Please refer to the Wire to verify the current version.

Appendix B – Structure with Condition Issues by Asset Category

Asset Component Category	Cause	Effect	Consequence	No. of Structures with condition issues
Conductor Fittings	Corrosion of fittings.	Fallen conductor	Bushfire resulting in potential loss of property and/or life Safety incident resulting in potential injury or death Line outage with potential network reliability impacts	1
Conductor Spacers	Minor repair required, damaged spacer.	Fallen conductor	Bushfire resulting in potential loss of property and/or life Safety incident resulting in potential injury or death Line outage with potential network reliability impacts	1
Earthwire Bonding	Minor repair required, earth bond has broken strands	Uncontrolled discharge or contact with electricity	Safety incident resulting in potential injury or death Line outage with potential network reliability impacts	6
Insulator	Non-ceramic insulators (NCI) have reached end of serviceable life.	Fallen conductor	Bushfire resulting in potential loss of property and/or life Safety incident resulting in potential injury or death Line outage with potential network reliability impacts	140
Public Safety – Aerial Marker Balls	Deteriorated.	Uncontrolled discharge or contact with electricity	Safety incident resulting in potential injury or death Line outage with potential network reliability impacts	1
Public Safety – Climbing Deterrents	Deteriorated.	Unauthorised access	Safety incident resulting in potential injury or death Line outage with potential network reliability impacts	1
Public Safety – Danger Signs	Deteriorated.	Unauthorised access	Safety incident resulting in potential injury or death Line outage with potential network reliability impacts	136
Public Safety - Structure Earthing	Erosion of ground has exposed earth strap.	Uncontrolled discharge or contact with electricity	Bushfire resulting in potential loss of property and/or life Safety incident resulting in potential injury or death	4
Tower Crossarm	Corrosion of tower members. Failure of critical members can compromise structural integrity.	Fallen structure and conductor	Bushfire resulting in potential loss of property and/or life Safety incident resulting in potential injury or death Line outage with potential network reliability impacts	0

Warning: A printed copy of this document may not be the current version. Please refer to the Wire to verify the current version.